



...manufacturing

Termtable
products.

Designed to give an ergonomic and flexible mounting platform for your payment terminal and prevent damage due to the traditional "back and forth" movements with each transaction.

Features

- Manufactured in robust mild steel
- Durable powder coated finish
- Smooth 60° tilt and 190° swivel action
- Dual cable entry options
- Flange cover to conceal fixing holes
- Screw or adhesive pad fixing options (screws provided)
- Supplied fully built for a simple install
- Upgradeable in the field with a simple top plate swap


Options

- Bespoke design service for special requirements
- Key lock option to guard against terminal theft
- Cable tethered unit for hand held terminals
- Swivel only units
- Different height poles

TO SUIT VERIFONE SECURA

Installation instructions

1. Select the desired position for your payment terminal.
2. Place the terminal stand on the countertop and choose whether the unit is best swivelling clockwise or anti-clockwise.
3. Position the base plate so that sufficient access can be gained to the terminal by both the customer and vendor when the unit is swivelled through it's 190°.
4. With a pencil or felt pen, mark through each hole onto the countertop.
5. If using the screws provided, drill a 2mm pilot hole in the countertop to accept the fixing screws. Please note that these screws are intended for use when fixing to a wood countertop, other fasteners may be required when fixing to different types of countertop material. If using the self adhesive pad fixing method, refer to the separate instruction sheet for use.



6. If the cables are to be fed through the bottom of the base pole then drill a large hole in the countertop to accept them. This is not necessary if the countertop cable entry is to be used.
7. With the power switched off, feed the cables through the desired base pole entry and up through the top exit of the pole. Ensure that sufficient cable length is fed through the top of the pole to allow connection to the terminal.
8. Screw the Termtable down to the countertop.
9. Connect the cables to the payment terminal.
10. Push the payment terminal into the cradle plate ensuring that the back is lined up as per the adjacent picture. Ensure the terminal is pushed down until all of the rubber feet touch the cradle plate.
11. Switch on the terminal power supply.

Ighten House
71-77 Dryden Street
Padiham
Lancashire
BB12 7EN.

T: 08000 488611
F: 08002 425731